

SWM 4000 Series Frequency Allocation Chart

Frequency : (902-928 MHz) Bandwidth: 26Mhz

Frequency Allocation (MHz)	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7
Channel 1	902.625	906.250	903.775	902.725	905.025		
Channel 2	906.900	907.425	907.625	904.625	907.775		
Channel 3	908.050	914.900	909.425	908.250	909.200		
Channel 4	912.800	917.500	916.000	911.950	911.075		
Channel 5	914.250	919.100	919.500	914.900	916.150		
Channel 6	915.975	921.875	921.100	922.750	922.750		
Channel 7	917.275	924.825	923.550	925.425	923.875		
Channel 8	925.325	926.800	925.625	927.575	927.700		
Channel 9							
Channel 10							
Channel 11							

Frequency M725: (710-740 MHz) Bandwidth: 30Mhz

Frequency Allocation (MHz)	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7
Channel 1	710.300	710.400	710.500	710.050	710.750	710.550	711.050
Channel 2	712.700	711.300	711.000	710.900	711.700	711.450	712.550
Channel 3	715.700	713.500	712.050	713.600	720.700	713.250	717.550
Channel 4	719.600	717.300	714.250	715.700	726.900	715.450	721.550
Channel 5	730.000	721.450	716.750	716.000	733.900	729.650	727.050
Channel 6	730.300	725.900	727.750	723.200	738.250	739.050	735.050
Channel 7	730.900	730.900	730.650	729.500			
Channel 8	732.100	739.150	739.450	738.000			
Channel 9							
Channel 10							
Channel 11							

Frequency M606: (606-630 MHz) Bandwidth: 24Mhz

Frequency Allocation (MHz)	Group 1	Group 2	Group 3	Group 4	Group 5	Group 6	Group 7
Channel 1	607.000	606.600	609.900	607.700	606.300	606.600	606.300
Channel 2	610.200	607.500	615.000	616.300	614.000	609.100	609.100
Channel 3	613.500	608.600	617.700	617.600	615.200	612.800	610.900
Channel 4	619.100	609.900	621.000	623.100	616.100	620.000	626.000
Channel 5	620.300	614.000	623.000	627.000	619.300	622.100	627.200
Channel 6	622.800	617.100	627.400			625.300	628.100
Channel 7	624.500	621.200					629.500
Channel 8	626.700	622.200					
Channel 9	627.600	627.100					
Channel 10	628.300	628.800					
Channel 11	629.100						

